www.harisongenerators.com

-HARISON

0

NOT JUST BACKUP WE PROVIDE CORE STRENGTH

SILENT FEATURES OF OUR GENERATORS :

- OPERATABLE FROM MOBILE
- ACOUSTIC ENCLOSURE
- ELECTRONIC GOVERNER
- SILENT & COMPACT
- MULTI FUNCTIONAL

HARISON

DIGITAL DISPLAY METER

Toll Free: 1800 121 5351

HARISON

7.5 KVA HG7.5KVA

MORE THAN JUST BACKUP



TECHNICAL SPECIFICATION FOR DURKATOSERIES

| GENERATOR SET SPECIFICATIONS | CPCBIV+ |
|--|---|
| PRIME POWER RATING | 7.5 kVA |
| KW | 6 kW |
| PHASE | 1P / 3P |
| RATED CURRENT | 32/10 |
| GEN SET MODEL | HG7.5KVA |
| VOLTAGE | 230V(1P)/415V(3P) |
| POWER FACTOR | 0.8 |
| FUEL CONSUMPTION@100% | 1.8 litres/hour |
| FUEL CONSUMPTION@75% | 1.6 litres/hour |
| FUEL CONSUMPTION@50% | 1.5 litres/hour |
| BATTERY STARTING VOLTAGE | 12 VDC |
| | |
| ENGINESPECIFICATIONS | HARISON ENGINE |
| ENGINE MODEL | HG5AZGLIV |
| CAPACITY OF ENGINE | 668 cc |
| RATED OUTPUT @100%LOAD | 10 BHP |
| NUMBER OF CYLINDERS | 1 |
| NO OF STROKES | 4 |
| BORE*STROKE | 100*85 |
| RATED SPEED | 3000 |
| TYPE OF ASPIRATION | Natural Aspiration |
| COOLING SYSTEM | Air Cooled |
| COOLANT CAPACITY | N.A. |
| TYPE OF GOVERNER | Mechanical |
| GOVERNOR CLASS | A2 |
| BATTERY CAPACITY | 35/45 AH & above |
| OVERLOAD CAPACITY | 10% Overloading is allowed after 10 Hours of continuous running |
| OIL SUMP CAPACITY | 1.2 LITRES |
| | |
| ALTERNATOR SPECIFICATIONS | |
| MAKE | NSM / MECCALTE |
| RATING | 7.5KVA |
| POWER FACTOR | 0.8 |
| ТҮРЕ | Brushless-IP 23 |
| VOLTAGE, VOLTS | 230V(1P)/415V(3P) |
| RATED SPEED | 3000 rpm |
| FREQUENCY,HZ | 50Hz |
| VOLTAGE REGULATIONS | VG 3 |
| CLASS OF INSULATION | H-Class |
| CONTROL PANEL | With both Inbuilt ATS/AMF and Manual Options |
| WAVE FORM DISTORTION/TOTAL HARMONIC DISTORTION | No Load<1.5% Non distortion Balanced Linear Load 5% |
| TELEPHONIC HARMONIC FACTOR | <2% |
| | - 70 |
| ACOUSTICS SPECIFICATIONS | |
| NOISE LEVEL | <75DBA @1meter distance |
| LENGTH | 1145 |
| WIDTH | 700 |
| HEIGHT | 775 |
| FUEL TANK CAPACITY (Approx) | 20 Liters & above |
| APPROX NET WEIGHT | 225KG |
| | |

* Automatic change over switch extra. (Optional / Where applicable / required/Extra charges applicable.) * Fuel consumptions are noted at standard conditions and may vary than mentioned.

MORE THAN JUST BACKUP

HARISON J SERIES * WITH IOT REMOTE OPERATING DEVICE

HARISON

ARISON GENERATORS PVT. LTD.

50

00000

DG

15 .

0.989 Energy 15 rue Puel Level 1500. wtery Voltage 12 v

240

BUY NOW

-HARISON

HARISON GENERATORS PVT. LTD. Plot No. 81, Daulatpur Industrial Area, Near Focal Point, Near Daulatpur Primary School, Patiala (147002) www.harisongenerators.com | info@harisongenerators.com



*Extra Charges Applicable

